




INTRODUCTION



- | | |
|---|---|
| 三相四线交流电源滤波器
Three-phase four-wire AC power filter | 含共模和差模线圈
With common mode and differential mode coil |
|  多种出线方式可供选择
Multiple connection to choose from |  多种安装方式可供选择
Multiple installation methods to choose from |

FEATURE

- | | |
|--|---|
|  CW12C- *A-S
螺丝固定螺栓出线滤波器
Screw bolt connection filter by screw fixed |  CW12C- *A-R
侧面导轨固定端子排出线滤波器
Terminal block connection filter by side guide rail fixed |
|  CW12C- *A-S(005)
螺丝固定端子排出线滤波器
Terminal block connection filter by screw fixed |  CW6C- *A-R
螺丝固定端子排出线滤波器
Terminal block connection filter by screw fixed |
|  CW6CL2-(3~85)A-R
螺丝固定欧式端子出线双极滤波器
European style terminal block connection bipolar filter by screw fixed | |

APPLICATION

- | | | |
|---|--|--|
| ■ 电子电气设备
Electrical and Electronic Equipment | ■ 医疗设备
Medical Equipment | ■ 办公自动化设备
Office Automation Equipment |
| ■ 消费电子
Consumer Electronic Production | ■ 数据通讯设备
Data Communication | ■ 变频器
Frequency converter |
| ■ 机械设备
Mechanical equipment | ■ 三相工业设备
Three-phase industrial
euiPMENT | ■ 各类电力设备
Power equipment of all kinds |

TECHNICAL DATA

- | | |
|---|--------------------------------------|
| ■ 额定电压 / Rated Voltage: 115/250/380/440V AC | ■ 工作频率 / Working Frequency: 50/60Hz |
| ■ 额定电流 / Rated Current: 1-85A | ■ 气候类型 / Climatic Category: 25/85/21 |
| ■ 测试电压 / Working Frequency: 1500V DC(Line to Line) 2000V AC(Line to Ground) | |

LIST

产品型号 Part No.	额定电流(A) Rate Current	泄露电流(mA) Leakage Current @250VAC 50Hz	电路图 Schematics	外形尺寸 Dimension	出线方式 Connection	安装方式 Installation	重量(g) Weigh	安规认证 Certification
CW12C-+A-S	3~60	<2.1	B11	A22		螺丝 Screw	970	CE RoHS CCC
CW12C-+A-S(005)	3/6/10/20/30	<2.1	B24	A49		螺丝 Screw	832	CE RoHS CCC
CW12C-+A-R	3/6/10/20/30	<2.1	B24	A50		导轨 Rail	835	CE RoHS CCC
CW6C-+A-R	40/50/60/70/80	<2.1	B24	A43		螺丝 Screw	2170	RoHS CE
CW6CL2-+A-R	3/6/10/20/30	<2.1	B18	A34		螺丝 Screw	2200	RoHS CE
CW6CL2-+A-R	40-85	<2.1	B18	A35		螺丝 Screw	4550	RoHS CE

DIMENSION



SCHEMATICS

