

产品介绍



YS36Q1AN-★A

- 单相交流电源滤波器
Single Phase AC Filters
 - 含共模线圈
With common mode coil
 - 欧式端子连接安全快捷
European style terminal block connected is safe and quick
 - 大电流滤波器
High current filter
 - 多种安装方式可供选择
Multiple installation methods to choose from

产品特点

- | | | | |
|---|---|---|---|
| CW12A-*A-R | 螺丝固定滤波器
Filter by screw fixed | YS36M1AN-*A | 螺丝固定滤波器
Filter by screw fixeded |
| YS36Q1AN-*A | 底部导轨固定滤波器
Filter by bottom guide rail fixed | | |

APPLICATION

- | | | |
|---|--|--|
|  电子电气设备
Electrical and Electronic Equipment |  医疗设备
Medical Equipment |  办公自动化设备
Office Automation Equipment |
|  消费电子
Consumer Electronic Production |  数据通讯设备
Data Communication |  其他电源产品等
Other Power Production... |

TECHNICAL DATA

- | | |
|--|---------------------------------------|
| ■ 额定电压 / Rated Voltage : 115/250V AC | ■ 工作频率 / Working Frequency : 50/60Hz |
| ■ 额定电流 / Rated Current : 1-85A | ■ 气候类型 / Climatic Category : 25/85/21 |
| ■ 测试电压 / Working Frequency : 1500V DC(Line to Line) 2000V AC(Line to Ground) | |

产品列表

产品型号 Part No.	额定电流(A) Rate Current	泄露电流(mA) Leakage Current @250VAC 50Hz	电路图 Schematics	外形尺寸 Dimension	出线方式 Connection	安装方式 Installation	重量(g) Weigh	安规认证 Certification
CW12A-*A-R	40/50/60/70/80/85	<0.5	B14	A28		螺丝 Screw	1089	CE RoHS
YS36M1AN-*A	40/50/60	<0.5	B14	A45		螺丝 Screw	341	CE RoHS
YS36Q1AN-*A	40/50/60	<0.5	B7	A48		导轨 Rail	341	CE RoHS

外形尺寸(mm)



SCHEMATICS

